

# CARD & QR CODE READER

MULTI-TECHNOLOGY RFID, NFC, BLUETOOTH® AND MATRIX CODES




Available in keypad or touchscreen versions



## BENEFITS

- Integrated QR code & contactless solution
- Quick reading of QR Codes printed or on your smartphone
- Backward compatible and interoperable



13.56 MHz



BLUETOOTH®



QR Code



TTL  
RS485



Water  
resistant  
EQ IP65



Vandal-proof  
IK08



YOUR LOGO

- Add your Logo
- 2 configurable multicolor LEDs

The Architect® Blue RFID, NFC, and Bluetooth® multi-technology reader is equipped with a QR Code module to enable the identification of employees and visitors.

Identification by QR Code simplifies the management of temporary access in offices, parking lots or any other infrastructure.

## SIMPLE AND EASY TO USE

The access control reader by QR Code Architect® Blue streamlines visitor access with ease and ultimate dual speed reading.

It guarantees QR Code-reading day and night and in all weather conditions: very bright environments, reflections, indoor or outdoor...

The ergonomic design of the reader enables feedback to the user: double visual led indicator, audible indicator, etc.

## MULTI-TECHNOLOGY READER

The reader facilitates the identification of users with different profiles (visitors, employees, tenants, drivers...) by its compatibility with multiple identification technologies.

### QR Code

Multi-formats supported (1D & 2D codes): QR Code, Micro QR Code, Code 128, Aztec, and Data Matrix. The QR Code can be printed or simply displayed on your smartphone (e-mails, virtual cards, etc.).

### Bluetooth® & NFC

The smartphone becomes your access key and removes all the limitations of traditional access control cards. STid offers 6 modes of Prox, long distance or hands-free identification to make your access control both secure and instinctive!

### RFID MIFARE® DESFire® EV2 & EV3

The reader supports the latest MIFARE® DESFire® EV2 & EV3 contactless technologies with new data security features: Secure Messaging EV2 and Proximity Check.

It supports the use of public security algorithms recognized by specialized and independent organizations in information security (ANSSI and FIPS).

## OPEN TECHNOLOGIES FOR EASY INTEGRATION

The reader is compatible with all access control systems and accepts multiple interfaces and protocols (Wiegand, Clock & Data, SSCP® and OSDP™).

The QR Code module can be installed on all existing compatible Architect® Blue readers.

## A CUSTOMIZED SCALABLE CONFIGURATION

The Architect® Blue reader can be customized to meet your needs: all the features and security levels of the readers in your organization can be upgraded.

The modularity allows to implement new functions such as a keypad or a touch screen.

## STANDING THE TEST OF TIME

The design of the reader makes it very robust in harsh environments. It can therefore be used outdoors and offers high levels of resistance to vandalism (certified IK08).

## SPECIFICATIONS

Operating frequency/Standards	13.56 MHz: ISO14443 types A & B, ISO18092 Bluetooth®																		
Technology compatibilities	MIFARE® Ultralight® & Ultralight® C, Classic & Classic EV1, Plus® (S/X) & Plus® EV1, DESFire® 256, EV1, EV2 & EV3, PicoPass® (CSN only), iCLASS™ (CSN only) STid Mobile ID® (NFC HCE and Bluetooth® virtual card), Orange Pack ID																		
Functions	Read only CSN and secure (file, sector) / Protocol driven (read write)																		
Communication interfaces & protocols	TTL Clock&Data (ISO2) or Wiegand output (encrypted option - S31) / RS485 output (encrypted option - S33) with secure SSCP® v1 and v2 communication protocols, OSDP™ v1 (plain communication) and v2 (SCP secure communication) Compatible with EasySecure interface																		
Matrix code reader	1D & 2D codes: QR Code versions 1, 2 and 3; Micro QR Code; code 128; Aztec and Data Matrix Different formats: hexadecimal; decimal; ASCII; raw (in OSDP™) Detection under ambient lighting from 0 to 100,000 LUX / 3 available modes: ECO; normal day and night; intense brightness Adjustable light beam / target brightness and detection sensitivity																		
Reading distances**	3 cm / 1.18" minimum with a QR Code (depending on the size of the code) Up to 8 cm / 3.15" with a MIFARE® DESFire® EV2 card Up to 20 m / 65.6 ft with a Bluetooth® smartphone (adjustable distances on each reader)																		
Data protection	Yes - EAL5+ secure data storage with certified crypto processor																		
Light indicator	2 RGB LEDs - 360 colors ▲ ▲ ▲ Configuration by card (standard or virtual), software or external command (0V) depending on interface																		
Audio indicator	Internal buzzer with adjustable intensity Configuration by card (standard or virtual), software or external command (0V) depending on interface																		
Relay	Automatic tamper direction management or SSCP® / OSDP™ command according to the interface																		
Power requirement	260 mA / 12 VDC max																		
Power supply	7 VDC to 28 VDC																		
Connections	10-pin plug-in connector (5 mm / 0.2") / 2-pin plug-in connector (5 mm / 0.2"); O/C contact - Tamper detection signal																		
Material	ABS-PC UL-V0 (black) / ASA-PC-UL-V0 UV (white)																		
Dimensions (h x w x d)	156.5 x 80 x 36 mm / 6.3" x 3.15" x 1.02" (general tolerance following ISO NFT 58-000 standard)																		
Operating temperatures	- 30°C to + 60°C / - 22°F to + 140°F																		
Tamper switch	Accelerometer-based tamper detection system with key deletion option (patented solution) and/or message to the controller																		
Protection / Resistance	IP65 Level - Weather-resistant with waterproof electronics (CEI NF EN 61086 homologation) / Humidity: 5 - 90% / Reinforced IK08 certified vandal-proof structure																		
Mounting	Compatible with any surfaces and metal walls - Wall mount/Flush mount: - European 60 & 62 mm / 2.36" & 2.44" - American (metal/plastic) - 83.3 mm / 3.27" - Dimensions: 101.6 x 53.8 x 57.15 mm / 3.98" x 2.09" x 2.24" - Examples: Hubbel-Raco 674, Carlon B120A-UP																		
Certifications	CE (Europe), FCC (USA), IC (Canada), UKCA (United Kingdom) and UL																		
Part numbers y: case color (1: black - 2 white)	<table border="0"> <tr> <td>Read only secure - TTL.....</td> <td>ARCS-R31-AQ/BT1-xx/y</td> </tr> <tr> <td>Read only secure / Secure Plus - TTL.....</td> <td>ARCS-S31-AQ/BT1-xx/y</td> </tr> <tr> <td>Read only secure - RS485.....</td> <td>ARCS-R33-AQ/BT1-7AB/y</td> </tr> <tr> <td>Read only secure / EasySecure interface - RS485.....</td> <td>ARCS-R33-AQ/BT1-7AA/y</td> </tr> <tr> <td>Read only secure / Secure Plus - RS485.....</td> <td>ARCS-S33-AQ/BT1-7AB/y</td> </tr> <tr> <td>Read only secure / Secure Plus / EasySecure interface - RS485.....</td> <td>ARCS-S33-AQ/BT1-7AA/y</td> </tr> <tr> <td>Controlled by SSCP® v1 - RS485.....</td> <td>ARCS-W33-AQ/BT1-7AA/y</td> </tr> <tr> <td>Controlled by SSCP® v2 - RS485.....</td> <td>ARCS-W33-AQ/BT1-7AD/y</td> </tr> <tr> <td>Controlled by OSDP™ v1 &amp; v2 - RS485.....</td> <td>ARCS-W33-AQ/BT1-7OS/y</td> </tr> </table>	Read only secure - TTL.....	ARCS-R31-AQ/BT1-xx/y	Read only secure / Secure Plus - TTL.....	ARCS-S31-AQ/BT1-xx/y	Read only secure - RS485.....	ARCS-R33-AQ/BT1-7AB/y	Read only secure / EasySecure interface - RS485.....	ARCS-R33-AQ/BT1-7AA/y	Read only secure / Secure Plus - RS485.....	ARCS-S33-AQ/BT1-7AB/y	Read only secure / Secure Plus / EasySecure interface - RS485.....	ARCS-S33-AQ/BT1-7AA/y	Controlled by SSCP® v1 - RS485.....	ARCS-W33-AQ/BT1-7AA/y	Controlled by SSCP® v2 - RS485.....	ARCS-W33-AQ/BT1-7AD/y	Controlled by OSDP™ v1 & v2 - RS485.....	ARCS-W33-AQ/BT1-7OS/y
Read only secure - TTL.....	ARCS-R31-AQ/BT1-xx/y																		
Read only secure / Secure Plus - TTL.....	ARCS-S31-AQ/BT1-xx/y																		
Read only secure - RS485.....	ARCS-R33-AQ/BT1-7AB/y																		
Read only secure / EasySecure interface - RS485.....	ARCS-R33-AQ/BT1-7AA/y																		
Read only secure / Secure Plus - RS485.....	ARCS-S33-AQ/BT1-7AB/y																		
Read only secure / Secure Plus / EasySecure interface - RS485.....	ARCS-S33-AQ/BT1-7AA/y																		
Controlled by SSCP® v1 - RS485.....	ARCS-W33-AQ/BT1-7AA/y																		
Controlled by SSCP® v2 - RS485.....	ARCS-W33-AQ/BT1-7AD/y																		
Controlled by OSDP™ v1 & v2 - RS485.....	ARCS-W33-AQ/BT1-7OS/y																		

## DISCOVER OUR CREDENTIALS AND ERGONOMIC MANAGEMENT TOOLS



13.56 MHz or dual frequency ISO cards & key holders



QR Codes, Bluetooth® & NFC smartphones using STid Mobile ID® application



SECARD configuration kit and SSCP® v1 & v2 and OSDP™ v1 & v2 protocols



Web platform for remote management of your virtual cards

\*Our readers only read the iCLASS™ chip serial number / UID PIC01444-3B. They do not read iCLASS™ cryptographic protection or the HID Global serial number / UID PIC01444-3B.

\*\*Caution: information about the distance of communication: measured from the center of the antenna, depending on the type of credential, size of the credential, operating environment of the reader, temperatures, power supply voltage and reading functions (secure reading). External interference may reduce reading distances.

Legal: STid, STid Mobile ID®, SSCP® and Architect® are registered trademarks of STid SAS. All trademarks mentioned in this document belong to their respective owners. All rights reserved - This document is the property of STid. STid reserves the right to make changes to this document and to cease marketing its products and services at any time and without notice. Photos are not contractually binding.

### Headquarters / EMEA

13850 Créasque, France  
Tel.: +33 (0)4 42 12 60 60

### PARIS-IDF

92290 Châtenay-Malabry, France  
Tel.: +33 (0)1 43 50 11 43

### STid UK Ltd.

Callows Hill, Warwick CV34 6UW, UK  
Tel.: +44 (0) 192 621 7884

### NORTH AMERICA

Irving, Texas 75063-2670, USA  
Tel.: +1 877 894 9135

### LATINO AMERICA

Cuahtémoc, 06600 CDMX, México  
Tel.: +52 (55) 5256 4706

### MIDDLE EAST

Dubai Digital Park, DSO, UAE  
Tel.: +971 521 863 656