

# SC-43-0200-0001-99

## SmartCell Contact Transmitter and Input Device for Information Zones

### Overview

---

The SmartCell Input Device is quick and easy to install and offers individual addressing at the SmartCell Control Panel. The device allows non fire to be monitored at the SmartCell Control Panel and to an information alert when activated. Examples may include the monitoring of doors (opening/closing), a loss of power to your fridge, flood detection and an alarm condition on your intruder system.

Features include a resistor monitored input, an alternative magnetic contact option and bidirectional 868 MHz communication.

This device is third party certified and compatible with the full SmartCell product range.



### Details

---

- Full wireless communication with panel
- Quick and easy to install
- Resistor monitored input
- Alternative magnetic contact option (magnet supplied)
- For connection to remote information devices
- NOT FOR FIRE OR SECURITY APPLICATIONS

# SC-43-0200-0001-99

## SmartCell Contact Transmitter and Input Device for Information Zones

### Technical specifications

#### General

Wireless frequency	868 MHz
--------------------	---------

#### Input

Input quantity	1
Input type and rating	Resistor monitored input

#### Physical

Physical dimensions	30 x 110 x 28 mm (W x H x D)
Net weight	0.05 kg
Colour	White
Mounting type	Wall mount
Batteries	1 x ER14505M 3.6 V lithium thionyl chloride battery (Fanso or Titus)

#### Environmental

Operating temperature	-10 to +55°C
Storage temperature	-10 to +30°C (with battery) -10 to +55°C (without battery)
Relative humidity	95% noncondensing max.
Environment	Indoor

#### Regulatory

Compliance	CE
Standards	R&TTE



As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit [firesecurityproducts.com](https://firesecurityproducts.com) online or contact your sales representative.