

ATS1290N

Intelligent Addressable Device System bus DGP (IADS bus)

Product Overview

The ATS1290N expander offers up to thirty-two addressable devices. Devices can be input or also include outputs. Addressable devices are powered through the 2 wire databus. Alternatively, devices can be powered from an external power supply. The addressable bus allows a free wiring topology, making it the best fit for retrofit installations.

Expanders

Expanders are used to expand the number of alarm inputs in an Advisor Advanced system. Expanders allow inputs and outputs/relays to be connected at a location remote from an Advisor Advanced panel. Expanders communicate via poll & reply messages. Detectors, door contacts and other detection devices are connected to expanders that report any change of state to the control panel for processing. Available expanders include support for conventional devices, wireless devices as well as intelligent addressable devices. A special expander is available providing expansion of four to eight intelligent doors or lifts.

System databus connection

The system databus is used to connect expanders as well as keypads and readers (RASs) to the Advisor Advanced control panel. Remote devices can be up to 1.5 km from a control panels when using the preferred wiring and cable types. Keypads, readers and expanders have to be connected via a 2 pair twisted and shielded data cable to the system databus connection to achieve this. (WCAT52 is recommended). Daisy chain is the preferred wiring method. The shield of the data cable should be connected to earth at the control panel and should be left disconnected at any other end.

Functionality

Expanders provide information from remote locations to Advisor Advanced control panels in structured records. Data collected ranges from a wired input state to wireless or addressable device dates to a door state.

Bus devices communicate with the control panel. If a failure in communication occurs, the expander remembers the last alarm in a system preventing loss of an alarm due to a short interruption in data communication.

Up to 15 or 30 expanders can be connected to an Advisor Advanced depending on the variant.



Details

- Unique 2/4 wire addressable bus
- Free wiring topology
- Use existing wiring in case of retrofit
- Device configuration through downloader
- Up to 32 addressable devices
- Device can have input and/or output
- ATS1644 plastic enclosure with tamper protection

ATS1290N

Intelligent Addressable Device System bus DGP (IADS bus)

Technical specifications

General

Expander type	Addressable Point ID (PID), Input expander
Product line	Advisor Advanced, ATS Master
Connection type	Databus connection
Max. distance from panel	1.5 km
Max. per panel	15

Inputs

Total	32
-------	----

Outputs

Total	32
-------	----

Electrical

Operating voltage	10.5 to 13.8 VDC
Power consumption	53 mA (no IADS module connected)
Integrated power supply	No

Environmental

Relative humidity	95% noncondensing
-------------------	-------------------

Regulatory

Certification	VdS
---------------	-----



As a company of innovation, Carrier Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 5 May 2023 - 9:32