# AN-307

### Perimeter Protection System Wire Fence Vibration Detector


AN-307 is a two channel wire fence vibration detector to protect up to 600m (2x 300m) of wire fence with up to 350m of SK special sensor cable per each channel in case someone wants to pass or break into the restricted area. AN-307COM is a vibration detector with RS-485 option.

The new DSIGP<sup>®</sup> technology makes this product unique. The alarm is triggered by vibrations of the wire fence but successfully elimanates: EMF (Electric and Magnetic Fields), normal wind, rain and other weather conditions, animal, vegetation and other disturbances.

The newest Wind/Temperature Sensor, an add-on for AN-306 and AN-307 makes AN Detectors the precisest Perimeter Protection System with lowest level of false alarms with dynamic sensitivity adjustment in case of very windy weather and significant drop of temperature.

#### Features


- 2 channels with up to 2x 300m of perimeter protection
- New DSIGP® technology, NEW Wind/Temp Sensor add-on
- Protection for Lightnings and other electrical disturbances
- 3D adjustments: Dynamic Sensitivity, No. of Beats and Time



Sensitivity, Beats and Time adjustements


Technical Specification

**Power consumption:** 



Special sensor cable wiring example

- RS-485 to RS-232, TCP/IP or USB communication
- Easy to install and simple to use
- Low Power Consumption (save up to 40%)
- Software for PC monitoring and precision settings



#### Accessories



SK-300/350/1000 Special sensor cable



K-307 Converters RS485 - **RS232** TCP/IP, USB



**Tie wraps** 

鞲

AC-300

Junction box



extending the RS-485 signal



**IBM/HP Servers** with professional CCTV Software

Master unit housing:	Aluminum waterproof (IP65)
Weight	970 g
Dimensions	175 x 80 x 60 mm
End unit housing:	Aluminum waterproof (IP65)
Weight	140 g
Dimensions	50 x 45 x 30 mm
Working temperature:	From -30°C to +70°C
Technology:	New unique DSIGP®
Power supply:	8.0 VDC to 18.0 VDC

Less than 1 W 3 relays, NC (2 if RS-485 is used)



**Relays:** 




**GSM Alarm System** & Communicator Cinterion Quad GSM module


JVC VN-V686WPBU Fast 360° Direct Drive 27/36x Zoom Motion detection

CCTV camera


Wind & Temp Sensor



# AN-307 to Control panel



## AN-307COM with RS-485 to TCP/IP or USB or RS-232



Ulica Mirka Vadnova 19, SI 4000 Kranj, Slovenija ph: 00 386 4 280 74 00, fax: 00 386 4 234 08 81 www.mars-commerce.com