

ICP-MAP0111 MAP Panel enclosure

Modular Alarm Platform 5000



The MAP Panel Enclosure Kit (ICP-MAP0111) contains one MAP Panel Enclosure, one MAP Hinged Mounting Plate, one MAP Panel Enclosure Tamper Switch, one MAP Enclosure Lockset, and one MAP AC Terminal Block.

Regulatory information

Region	Regulatory compliance/quality marks	
Europe	CE	
France	AFNOR	1133400003A1
Europe	EN50131	G111040 Grade 3
Poland	TECHOM	03-16-o [ICP-MAP5000]
Germany	VdS	G111040 Class C
	VdS	G114801 Class C MAP 5000 COM
	VdS-S	S 112016

Parts included

Quantity	Component
1	Enclosure assembly
1	Accessory pack <ul style="list-style-type: none"> 1 MAP Panel Enclosure Tamper Switch (ICP-MAP0050) 1 MAP AC Terminal Block (ICP-MAP0065)

- ▶ Suitable for a main panel, a DE module, a power supply, 2x 40 Ah batteries and 4x LSN gateways
- ▶ Includes a hinged mounting plate

Quantity	Component
	<ul style="list-style-type: none"> 1 MAP Enclosure Lockset (ICP-MAP0060)
1	Hardware pack <ul style="list-style-type: none"> 7 TORX screws (M4 x 8 mm, Type A) 2 TORX screws (M3 x 5 mm) Spiral wrap (large size)
1	Literature – Installation Template
1	Drill template

Technical specifications

Mechanical

Dimensions (H x W x D) (mm)	658 mm x 443 mm x 193.50 mm
Weight (g)	1,566 g
Material	Steel
Color	White

Environmental

IP rating	IP31; IP30
Impact protection	IK06
Environmental class (EN 50130-5)	II

Environmental class (VdS 2110)	II
Usage	Indoor

Ordering information

ICP-MAP0111 MAP Panel enclosure

Kit contains one MAP Panel Enclosure, one MAP Hinged Mounting Plate, one MAP Panel Enclosure Tamper Switch, one MAP Enclosure Lockset, and one MAP AC Terminal Block.

Order number **ICP-MAP0111 | F.01U.300.119**

Accessories

ICP-MAP0020 MAP accessory mounting plate

Accessory mounting plate which can carry up to two MAP 12V Converters and one SIV Fuse Plate or an AT 2000 module.

Order number **ICP-MAP0020 | F.01U.073.081**

ICP-MAP0021 MAP EMIL, adapter plate

Order number **ICP-MAP0021 | F.01U.303.204**

ICP-MAP0050 MAP Panel/power enclosure, tamper switch

Fits in the MAP Panel and MAP Power Enclosures.

Order number **ICP-MAP0050 | F.01U.217.039**

SIV 28 MAP 28V fuse protected power distributor

For monitored fusing of the devices connected to a panel like e.g. MAP5000, up to 5 fuses

Order number **SIV 28 | F.01U.500.442**

ICP-MAP0065 MAP Terminal block

Terminal block to connect supply voltage to the MAP power supply 150W.

Order number **ICP-MAP0065 | F.01U.076.162**

ICP-MAP0090 MAP Spare cable kit

Cable kit containing cables and parts for electrical connections of MAP devices.

Order number **ICP-MAP0090 | F.01U.100.266**

ICP-MAP0060 MAP Enclosure lockset

Lock, two keys, and two warranty seals for use on MAP Panel Enclosure, MAP Power Enclosure, or MAP Expansion Enclosure.

Order number **ICP-MAP0060 | F.01U.074.338**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Tel.: +49 (0)89 6290 0
Fax: +49 (0)89 6290 1020
de.securitysystems@bosch.com
www.boschsecurity.com

North America:
Bosch Security Systems, LLC
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com